## ASSEMBLY INSTRUCTIONS COMPONENT STANDS



NOTE: Hand tighten all nuts and bolts until unit is complete. Tightening with a wrench as the unit is built may cause complications. Take caution when using metal tools to avoid damage to the painted surfaces of your unit.

- 1. UNWRAP ALL COMPONENTS. Verify that you have all parts required for assembly. Check the parts reference chart below.
- 2. PRE ASSEMBLY. If you purchased casters or spikes for your component stand, install them first on the base using the bolts and nuts included with either package. You will find four holes on the flanges of the base for either casters or spikes. If neither are installed, you may attach the enclosed rubber caps to the holes of the base to protect hard surface floors.
- 3. ATTACH SIDE PANELS TO BASE. To attach a side panel to the base, insert a SHORT bolt through the bottom of the base and fasten using a cap nut on the top of the hole. See Figure A.
- 4. BACK PANEL/CORD COLLECTOR ASSEMBLY. To assemble the back panel and cord collector to the base, insert a long bolt through the bottom of the hole and fasten using a cap nut on top. Note the cord collector piece is optional; if used, it should be the top layer. See Figure B.
- 5. ADD A SHELF. Insert a long bolt through the bottom of the hole on the lower shelf side panel, through the shelf hole and into the hole of the upper shelf side panel. See Figure C. Refer to Step 4 for back panel assembly. Repeat for each new shelf package.
- 6. ADD THE TOP SHELF. Insert a short bolt through the bottom of the hole in the side panel, through the hole in the top shelf and fasten with a cap nut. See figure D. Refer to Step 4 for back panel assembly.

To upgrade your stand by adding a shelf, casters or spikes please visit www.boltz.com. If you have any questions, please call us toll-free at 877.804.7650 (M-F 8:30am-5:30pm PT) or email us at customerservice@boltz.com.











